EQUIPMENT SCHEDULE

DEVICE	DEVICE DESCRIPTION	VOLTAGE	PH	KW	FLA	HP	STARTER / DISCONNECT TYPE	SIZE	FUSE	PLUG CONFIG	RECEPT CONFIG	FEEDER SIZE	NOTES
UNIT A	APARTMENT TYPE A	208 V	1										
UNIT B	APARTMENT TYPE B	208 V	1										
UNIT C	APARTMENT TYPE C	208 V	1										
UNIT D	APARTMENT TYPE D	208 V	1										
UNIT E	APARTMENT TYPE E	208 V	1										
UNIT F	APARTMENT TYPE F	208 V	1										
UNIT G	APARTMENT TYPE G	208 V	1										

LUMINAIRE SCHEDULE

TYPE NO	DESCRIPTION / SPEC NO	TOTAL WATTS	VOLT	MOUNTING	NOTES
		32 VA			
A1	2X4 - FLAT PANEL - 3000 LUMENS LITHONIA EPANL 2X4 3000LM 80CRI 40K MIN1 EZT MVOLT	26 VA	MVOLT	CEILING	
A2	2X4 - FLAT PANEL - 4000 LUMENS LITHONIA EPANL 2X4 4000LM 80CRI 40K MIN1 EZT MVOLT	39 VA	MVOLT	CEILING	
A3G	2X4 - FLAT PANEL - 4800 LUMENS - GASKETED LITHONIA EPANL 2X4 4800LM 80CRI 40K MIN1 EZT MVOLT	47 VA	MVOLT	CEILING	
A3G-EM	2X4 - FLAT PANEL - 4800 LUMENS -GASKETED LITHONIA EPANL 2X4 4800LM 80CRI 40K MIN1 EZT MVOLT	47 VA	MVOLT	CEILING	
A4	2X2 - FLAT PANEL - 2000 LUMENS LITHONIA EPANL 2X2 2000LM 80CRI 40K MIN1 EZT MVOLT	17 VA	MVOLT	CEILING	
B1	2X4 - BASKET - 3000 LUMENS LITHONIA 2VTL4 30L ADPT EZ1 LP840	27 VA	MVOLT	CEILING	
B2	2X4 - BASKET - 4000 LUMENS LITHONIA 2VTL4 40L ADPT EZ1 LP840	34 VA	MVOLT	CEILING	
B4	2X2 - BASKET - 2000 LUMENS LITHONIA 2VTL2 20L ADPT EZ1 LP840	18 VA	MVOLT	CEILING	
B4E	2X2 - BASKET - 2000 LUMENS - EMERGENCY LITHONIA 2VTL2 20L ADPT EZ1 LP840	18 VA	MVOLT	CEILING	
C1	6" RECESSED CAN - 1000 LUMENS LITHONIA LDN6 40 10 LO6 AR LSS MVOLT EZ1	13 VA	MVOLT	CEILING	
I1	INDUSTRIAL STRIP LED - 4' - 5000 LUMEN - ZL1N LITHONIA ZL1N L48 5000LM FST MVOLT 40K 80CRI WH ZACVH	34 VA	MVOLT	SURFACE / CABLE	
P1	PENDANT CYLINDER - 6" - 1000 LUMEN LDN6CYL 40 10 LO6 AR LSS MVOLT	13 VA	MVOLT		
S1	SITE POLE LIGHT LITHONIA DSX1 LED P5 50K T2M MVOLT HS	138 VA	MVOLT		
W1	WALL SCONCE	32 VA	120 V		
W2	2' WALL MOUNTED RECTANGULAR	32 VA	120 V		
WP1	WALL MOUNT CAN SYMBOL / WALL PACK	32 VA	120 V		

GENERAL EQUIPMENT SCHEDULE NOTES:

A. MOUNT ALL DISCONNECTS AND STARTERS ON UNIT UNLESS SHOWN OTHERWISE. MOUNT ALL WITH CLEARANCES AS PER NEC COORDINATE WITH MECHANICAL.

B. SFT = FUSETRON BOX COVER UNIT (BUSS #SSU OR EQUAL) WITH FUSE.

C. STE = THERMAL ELEMENT SWITCH. PROVIDE THERMAL UNIT.

D. EXP = DEVICE TO BE EXPLOSION-PROOF.

E. FVNR = FULL VOLTAGE NON-REVERSING MOTOR STARTER.

F. CS/NFD, FD = COMBINATION STARTER/ NON OR FUSED DISCONNECT SWITCH.

G. NFD OR FD = NON OR FUSED DISCONNECT SWITCH.

H. ALL SWITCHES, DISCONNECTS, ETC SHALL BE LOCKABLE.

I. ALL SWITCHES, DISCONNECTS, ETC SHALL BE NEMA 3R WHERE REQUIRED.

J. PROVIDE FUSES AS SHOWN; REVISE SIZES PER ACTUAL NAMEPLATE DATA.

K. STARTER ACCESSORIES:STARTER ACCESSORIES:
   1. CONTROL TRANSFORMER
   2. H-O-A SWITCH
   3. RED RUN LIGHT
   4. 2 NO CONTACTS; 2 NC CONTACTS

EQUIPMENT SCHEDULE NOTES:

1. THIS SCHEDULE LINE-ITEM DISPLAYS SIZING INFORMATION THAT IS GENERIC IN NATURE. SCHEDULE DOES NOT ITEMIZE ALL INSTANCES OF EQUIPMENT. CONTRACTOR SHALL REFER TO THE PLANS FOR FINAL QUANTITIES AND LOCATIONS.

LUMINAIRE SCHEDULE NOTES:

1. VERIFY CHAIN LENGTH AND ADJUST ACCORDINGLY.
2. COORDINATE MOUNTING HEIGHT BEFORE ROUGH-IN.
3. MOUNT ABOVE MIRROR.
4. SEE ARCHITECTURAL PLANS OR BUILDING ELEVATIONS.
5. PROVIDE STEM MOUNTED WHEN REQUIRED AT CEILING MOUNTED UTILITIES.
6. (2) BALLASTS; MOUNT ABOVE DOOR HEIGHT AT APPROX. 8'.
7. MOUNT REMOTE WALL BRACKET WHERE DIRECTED.
8. COORDINATE THE ACTUAL LOCATION WITH ELEVATOR DETAIL.
9. PROVIDE GYPSUM TRIM RING WHERE REQUIRED. (SUPPORT TRIM RING FROM STRUCTURE.) SEE ARCH A6 SERIES SHEETS FOR REFLECTED CEILING PLANS.
10. PROVIDE BODINE #B50/2L (OR EQUAL) EMERGENCY BALLAST WHERE INDICATED ON PLAN. CONNECT 2 LAMPS TO BALLAST.
11. PROVIDE SEPARATE BALLAST WHERE DUAL LEVEL SWITCHING IS INDICATED ON PLANS.
12. PROVIDE BODINE #B426/2L (OR EQUAL) EMERGENCY BALLAST WHERE INDICATED ON PLANS. CONNECT 2 LAMPS TO BALLAST.

ISSUE DATE: PROJECT ISSUE DATE
REVISIONS:
No.: DATE: BY: DESCRIPTION:

DESIGNED: DES
DRAWN: DRW
CHECKED: CHK

THIS DRAWING IS BEING MADE AVAILABLE BY SCHEMMER FOR REVIEW AND USE IN ACCORDANCE WITH THE AGREEMENT BETWEEN SCHEMMER AND THE RECIPIENT AND MAY NOT BE USED FOR ANY USE OF THIS DRAWING OTHER THAN THAT PERMITTED IN ACCORDANCE WITH THE AGREEMENT.

PRELIM - NOT FOR CONTSTRUCTION

SCHEMMER
Design with Purpose. Build with Confidence.

CLIENT NAME
PROJECT NAME
ADDRESS (OPEN PROJECT INFO TO ENTER)
ADDRESS

LUMINAIRE & EQUIPMENT SCHEDULES

PROJECT NO.:

E701